



TEI0001 Test Board

Revision v.14

Exported on 2022-04-22

Online version of this document:

<https://wiki.trenz-electronic.de/display/PD/TEI0001+Test+Board>

1 Table of Contents

1	Table of Contents	2
2	Table of Figures	3
3	Table of Tables	4
4	Overview	6
4.1	Key Features	6
4.2	Revision History	6
4.3	Release Notes and Know Issues	7
4.4	Requirements	7
4.4.1	Software	7
4.4.2	Hardware	7
4.5	Content	8
4.5.1	Design Sources	8
4.5.2	Prebuilt	9
4.5.3	Download	9
5	Design Flow	10
6	Launch	11
6.1	Programming	11
6.1.1	MAX10 Flash	11
6.1.2	JTAG	11
6.2	Usage	11
6.2.1	UART	11
7	System Design - Quartus	12
7.1	Block Design	12
8	Software Design - SDK	14
8.1	Application	14
8.1.1	test_board	14
9	Appx. A: Change History and Legal Notices	15
9.1	Document Change History	15
9.2	Legal Notices	15
9.3	Data Privacy	15
9.4	Document Warranty	16
9.5	Limitation of Liability	16
9.6	Copyright Notice	16
9.7	Technology Licenses	16
9.8	Environmental Protection	16
9.9	REACH, RoHS and WEEE	16

2 Table of Figures

Figure 1: Block Design - Project12

Figure 2: Block Design - Platform Designer12

3 Table of Tables

Table 1: Design Revision History	6
Table 2: Known Issues.....	7
Table 3: Software	7
Table 4: Hardware Modules	8
Table 5: Hardware Carrier.....	8
Table 6: Additional Hardware.....	8
Table 7: Design sources	9
Table 8: Prebuilt files (only on ZIP with prebuilt content)	9
Table 9: Document change history.	15

4 Overview

NIOS II Design with SDRAM controller, flash memory test and different LED sequences.

Refer to <http://trenz.org/max1000-info> for the current online version of this manual and other available documentation.

4.1 Key Features

- Quartus Prime Lite 20.1
- NIOS II
- SPI
- UART
- User Flash memory
- SDRAM memory
- 3-axis Accelerometer
- User LEDs
- User buttons

4.2 Revision History

Date	Quartus	Project Built	Authors	Description
2021-07-09	20.1 Lite	TEI0001-test_board_noprebuilt-quartus_20.1.1-20210709113727.zip TEI0001-test_board-quartus_20.1.1-20210709113644.zip	Thomas Dück	<ul style="list-style-type: none"> • update to Quartus Prime Lite 20.1 • TE scripts update
2020-10-19	19.1 Lite	TEI0001-test_board_noprebuilt-quartus_19.1.0-20201019101714.zip TEI0001-test_board-quartus_19.1.0-20201019101651.zip	Thomas Dück	<ul style="list-style-type: none"> • bugfixes
2020-07-07	19.1 Lite	TEI0001-test_board_noprebuilt-quartus_19.1.0-20200707153033.zip TEI0001-test_board-quartus_19.1.0-20200707153205.zip	Thomas Dück	<ul style="list-style-type: none"> • bugfixes • script update
2020-05-12	19.1 Lite	TEI0001-test_board_noprebuilt-quartus_19.1.0-20200512095852.zip TEI0001-test_board-quartus_19.1.0-20200512100037.zip	Thomas Dück	<ul style="list-style-type: none"> • 19.1 update

Date	Quartus	Project Built	Authors	Description
2019-11-11	18.1	TEI0001-test_board_noprebuilt-quartus_18.1-20191111104201.zip TEI0001-test_board-quartus_18.1-20191111104348.zip	Thomas Dück	<ul style="list-style-type: none"> add bash files for Linux OS
2019-10-28	18.1	TEI0001-test_board_noprebuilt-quartus_18.1-20191028120819.zip TEI0001-test_board-quartus_18.1-20191028120521.zip	Thomas Dück	<ul style="list-style-type: none"> create project with TE scripts new assembly variants
2019-04-02	18.1	TEI0001-03-08-C8-test_board-quartus_18.1-20190402.zip	Thomas Dück	<ul style="list-style-type: none"> initial release

Table 1: Design Revision History

4.3 Release Notes and Known Issues

Issues	Description	Workaround	To be fixed version
No known issues	---	---	---

Table 2: Known Issues

4.4 Requirements

4.4.1 Software

Software	Version	Note
Quartus Prime Lite	20.1	needed
NIOS II SBT for eclipse	---	optional

Table 3: Software

4.4.2 Hardware

Complete List is available on <project folder>/board_files/*_devices.csv

Design supports following modules:

Module Model	Board Part Short Name	PCB Revision Support	DDR	QSPI Flash	Others	Notes
TEI0001-03-08-C8*	08_C8_8MB	REV02, REV03	8MByte	64MBit	NA	NA
TEI0001-03-16-C8	16_C8_8MB	REV02, REV03	8MByte	64MBit	NA	NA
TEI0001-03-16-C8A	16_C8A_32MB	REV03	32MByte	64MBit	NA	NA
TEI0001-03-16-C8P	16_C8P_8MB	REV03	8MByte	64MBit	NA	NA

Table 4: Hardware Modules

*used as reference

Design supports following carriers:

Carrier Model	Notes

Table 5: Hardware Carrier

*used as reference

Additional HW Requirements:

Additional Hardware	Notes
USB cable for JTAG/UART	Check Carrier Board and Programmer for correct type

Table 6: Additional Hardware

4.5 Content

For general structure and of the reference design, see [Project Delivery - Intel devices](#)¹

4.5.1 Design Sources

¹ <https://wiki.trenz-electronic.de/display/PD/Project+Delivery+-+Intel+devices>

Type	Location	Notes
Quartus	<project folder>/source_files/quartus <project folder>/source_files/<Board Part Short Name>/quartus	Quartus project will be generated by TE Scripts optional, source files for specific assembly variants
Software	<project folder>/source_files/software <project folder>/source_files/<Board Part Short Name>/software	Additional software will be generated by TE Scripts optional, source files for specific assembly variants

Table 7: Design sources

4.5.2 Prebuilt

File	File-Extension	Description
SOPC Information File	*.sopcinfo	File with description of the *.qsys file to create software for the target hardware
Programmer Object File	*.pof	FPGA configuration file
Diverse Reports	---	Report files in different formats
Software Application File	*.elf	Software application for NIOS II processor system

Table 8: Prebuilt files (only on ZIP with prebuilt content)

4.5.3 Download

Reference Design is only usable with the specified Quartus version. Do never use different versions of Quartus software for the same project.

Reference Design is available on:

- [TEI0001 "Test Board" Reference Design²](https://shop.trenz-electronic.de/Download/?path=Trenz_Electronic/Modules_and_Module_Carriers/2.5x6.15/TEI0001/Reference_Design/20.1/test_board)

² https://shop.trenz-electronic.de/Download/?path=Trenz_Electronic/Modules_and_Module_Carriers/2.5x6.15/TEI0001/Reference_Design/20.1/test_board

5 Design Flow

⚠ Reference Design is available with and without prebuilt files. It's recommended to use TE prebuilt files for first launch.

Trenz Electronic provides a tcl based built environment based on Quartus Design Flow.


See also:

- [Project Delivery - Intel devices](#)³

The Trenz Electronic FPGA Reference Designs are TCL-script based projects. To create a project, open a project or program a device execute "create_project_win.cmd" on Windows OS and "create_project_linux.sh" on Linux OS.

TE Scripts are only needed to generate the quartus project, all other additional steps are optional and can also be executed by Intel Quartus/SDK GUI. For currently Scripts limitations on Win and Linux OS see: [Project Delivery - Intel devices](#) → [Currently limitations of functionality](#)⁴

1. Open create_project_win.cmd/create_project_linux.sh:




2. Select Board in "Board selection"
3. Click on "Create project" button to create project
 - a. (optional for manual changes) Select correct quartus installation path in "<project folder>/settings/design_basic_settings.tcl"

³ <https://wiki.trenz-electronic.de/display/PD/Project+Delivery+-+Intel+devices>

⁴ <https://wiki.trenz-electronic.de/display/PD/Project+Delivery+-+Intel+devices#ProjectDelivery-Inteldevices-Currentlylimitationsoffunctionality>

6 Launch

6.1 Programming

 Check Module and Carrier TRMs for proper HW configuration before you try any design.

6.1.1 MAX10 Flash

1. Connect the Module to USB-Port
2. Open `create_project_win.cmd/create_project_linux.sh`
3. Select correct board in "Board selection"
4. Click on "Program device" button
 - a. if prebuilt files are available: select "Program prebuilt file"
 - b. using own generated programming file: select "Program other file" and click on "Browse ..." to open own generated programming file
 - c. (optional) click on "Open programmer GUI" to program device with Quartus programmer GUI
5. Click on "Start program device" button

6.1.2 JTAG

Not used on this example.

6.2 Usage

1. Prepare Hardware like described on section [Programming](#)(see page 11)
2. Connect UART USB (most cases same as JTAG)

6.2.1 UART

1. Open Serial Console (e.g. PuTTY)
 - a. COM Port: Win OS see device manager, Linux OS see `dmesg | grep tty` (UART is *USB1)
 - b. Speed: 115200
2. Press reset button
3. Console output depends on used Software project, see [Software Design - SDK#Application](#)(see page 14)

7 System Design - Quartus

7.1 Block Design

The block designs may differ depending on the assembly variant.




Figure 1: Block Design - Project



8 Software Design - SDK

8.1 Application

Used software project depends on board assembly variant. Template location: <project folder>/source_files/software/

8.1.1 test_board

Software example to test TEI0001 module.

- You can toggle between following modes by pressing user button
 - a. Spirit level
 - b. Winbond SPI flash memory test
 - c. Shift register sequence
 - d. Knightrider sequence
 - e. Case statement sequence

9 Appx. A: Change History and Legal Notices

9.1 Document Change History

To get content of older revision got to "Change History" of this page and select older document revision number.


Date	Document Revision	Authors	Description
 2021-07-09	v.14 (see page 5)	Thomas Dück ⁵	<ul style="list-style-type: none"> • update to Quartus Prime Lite 20.1 • document style update • script update
2020-10-09	v.12	Thomas Dück	<ul style="list-style-type: none"> • bugfixes • script update
2020-05-13	v.10	Thomas Dück	<ul style="list-style-type: none"> • 19.1 release
2019-11-11	v.8	Thomas Dück	<ul style="list-style-type: none"> • add bash files for Linux OS
2019-10-29	v.6	Thomas Dück	<ul style="list-style-type: none"> • change design to TE scripts • new variants
2019-04-03	v.4	Thomas Dück	<ul style="list-style-type: none"> • Initial release 18.1
--	all	Thomas Dück ⁶	--

Table 9: Document change history.

9.2 Legal Notices

9.3 Data Privacy

Please also note our data protection declaration at <https://www.trenz-electronic.de/en/Data-protection-Privacy>

⁵ <https://wiki.trenz-electronic.de/display/~t.dueck>

⁶ <https://wiki.trenz-electronic.de/display/~t.dueck>

9.4 Document Warranty

The material contained in this document is provided “as is” and is subject to being changed at any time without notice. Trenz Electronic does not warrant the accuracy and completeness of the materials in this document. Further, to the maximum extent permitted by applicable law, Trenz Electronic disclaims all warranties, either express or implied, with regard to this document and any information contained herein, including but not limited to the implied warranties of merchantability, fitness for a particular purpose or non infringement of intellectual property. Trenz Electronic shall not be liable for errors or for incidental or consequential damages in connection with the furnishing, use, or performance of this document or of any information contained herein.

9.5 Limitation of Liability

In no event will Trenz Electronic, its suppliers, or other third parties mentioned in this document be liable for any damages whatsoever (including, without limitation, those resulting from lost profits, lost data or business interruption) arising out of the use, inability to use, or the results of use of this document, any documents linked to this document, or the materials or information contained at any or all such documents. If your use of the materials or information from this document results in the need for servicing, repair or correction of equipment or data, you assume all costs thereof.

9.6 Copyright Notice

No part of this manual may be reproduced in any form or by any means (including electronic storage and retrieval or translation into a foreign language) without prior agreement and written consent from Trenz Electronic.

9.7 Technology Licenses

The hardware / firmware / software described in this document are furnished under a license and may be used / modified / copied only in accordance with the terms of such license.

9.8 Environmental Protection

To confront directly with the responsibility toward the environment, the global community and eventually also oneself. Such a resolution should be integral part not only of everybody's life. Also enterprises shall be conscious of their social responsibility and contribute to the preservation of our common living space. That is why Trenz Electronic invests in the protection of our Environment.

9.9 REACH, RoHS and WEEE

REACH

Trenz Electronic is a manufacturer and a distributor of electronic products. It is therefore a so called downstream user in the sense of [REACH](http://guidance.echa.europa.eu/)⁷. The products we supply to you are solely non-chemical products (goods). Moreover and under normal and reasonably foreseeable circumstances of application, the goods supplied to you shall not release any substance. For that, Trenz Electronic is obliged to neither register nor to

⁷ <http://guidance.echa.europa.eu/>

provide safety data sheet. According to present knowledge and to best of our knowledge, no **SVHC (Substances of Very High Concern) on the Candidate List**⁸ are contained in our products. Furthermore, we will immediately and unsolicited inform our customers in compliance with REACH - Article 33 if any substance present in our goods (above a concentration of 0,1 % weight by weight) will be classified as SVHC by the **European Chemicals Agency (ECHA)**⁹.

RoHS

Trenz Electronic GmbH herewith declares that all its products are developed, manufactured and distributed RoHS compliant.

WEEE

Information for users within the European Union in accordance with Directive 2002/96/EC of the European Parliament and of the Council of 27 January 2003 on waste electrical and electronic equipment (WEEE).

Users of electrical and electronic equipment in private households are required not to dispose of waste electrical and electronic equipment as unsorted municipal waste and to collect such waste electrical and electronic equipment separately. By the 13 August 2005, Member States shall have ensured that systems are set up allowing final holders and distributors to return waste electrical and electronic equipment at least free of charge. Member States shall ensure the availability and accessibility of the necessary collection facilities. Separate collection is the precondition to ensure specific treatment and recycling of waste electrical and electronic equipment and is necessary to achieve the chosen level of protection of human health and the environment in the European Union. Consumers have to actively contribute to the success of such collection and the return of waste electrical and electronic equipment. Presence of hazardous substances in electrical and electronic equipment results in potential effects on the environment and human health. The symbol consisting of the crossed-out wheeled bin indicates separate collection for waste electrical and electronic equipment.

Trenz Electronic is registered under WEEE-Reg.-Nr. DE97922676.

 2019-06-07

⁸ <https://echa.europa.eu/candidate-list-table>

⁹ <http://www.echa.europa.eu/>